MDC Data Sheet

If TX Messenger is not up and running click on the TX Messenger Icon. (Lower left of Desktop)

If computer needs to be rebooted, at start up you will need to enter the password: lafire (in lower case)

Work from the left side of screen and press "DESK" to type commands

Func-1 XMIT: Transmit (the equivalent of "Enter")

Func-2 INC: Incident info for the incident assigned.

Func-3 ENR: Enroute (The Motro Floor Captain must attach you to the incident first)

Func-4 ONS: On Scene

Func-7 AVR: Available Radio (after an incident) Press Func-7, 2 times.

Func-8 LOC: Location, you will be prompted to enter 205Q for in "Quarters" at S&M or 205R for "Radio" at S&M.

If you are away from S&M, you can enter a Fire Station District number and R. Example: If you are at Fire Station 88, press 88R for "Radio" at FS-88.

Func-9 QTR: In quarters (you will be prompted for location, S&M is 205)

Func-11 USTAT: Get status of any unit (It will show you the last 10 status updates for the unit) This will be sent as a "Message" select Messages on left side of screen to view.

To get incident info:

UNIT ID of a unit assigned or INCIDENT NUMBER + Func-2. Example: (Engine 10) E10 + Func-2 (Incident 565) 565 + Func-2

To find the status of a unit (USTAT): UNIT ID + Func-11 Example: (Engine 10) E10 + Func-11. (It will show you the last 10 status updates for the unit) This will be sent as a "Message" select Messages on left side of screen.

To locate BC and DC Status (will show the Incident number if assigned to an incident so you can get more info): Type: CHF + Func-1.

To clear the screen press "Clear" on lower screen menu area.

METRO FLOOR CAPTAIN phone number 213-576-8920